

DIMMER COMPATIBILITY LINE

BASIC INFORMATION:

1. WHAT IS THE PRODUCT CODE AND WHERE DO I FIND IT?

The product code describes the lamp type. It contains 7 letters and digits and is starting with "A". Below an example for the product code of the stamp of the lamp:



2. HOW CAN I READ THE FOLLOWING CHARTS?

Legend:
Information about the dimmability of the lamps. Green means very good dimmability, yellow means limited dimmability, red means undesired dimmability etc.

List of dimmers tested in laboratory conditions

Legend					SUPERSTAR PAR16 35 36°				SUPERSTAR PAR16 50 36°				SUPERSTAR PAR16 80 36°				SUPERSTAR PAR16 80 120°			
Very good dimmability with indicated number of lamps (dimming range greater than 75%)																				
Limited dimmability with indicated number of lamps (dimming range smaller than 75%)																				
Undesired dimmability																				
Not relevant																				
Not tested																				
Dimmer					EAN/Basic Code		EAN/Basic Code		EAN/Basic Code		EAN/Basic Code		EAN/Basic Code		EAN/Basic Code		EAN/Basic Code			
Brand	Model	Voltage range	Power	Type	Number of Lamps	Dimming range	Number of Lamps	Dimming range	Number of Lamps	Dimming range	Number of Lamps	Dimming range	Number of Lamps	Dimming range	Number of Lamps	Dimming range				
ABB	STD 50-3	230V50Hz	60-500	L	1-20	98% - 15%	1-13	98% - 20%	1-8	97% - 23%	1-8	97% - 23%	1-20	98% - 15%	2-20	97% - 12%	2-20	98% - 16%		
Altenburger Electronic	50_30	230V50Hz	15-350	T	1-10	98% - 15%	2-10	97% - 1%	1-4	96% - 1%	1-4	96% - 1%	1-20	98% - 1%	2-9	98% - 1%	1-6	97% - 9%		
ALPORA	DSP 400	230V50Hz	400	L	1-20	98% - 27%	1-20	98% - 26%	1-20	97% - 27%	1-20	97% - 27%	1-15	98% - 1%	1-10	97% - 5%	1-6	94% - 7%		
Berker	2861	230V50Hz	50-420	U	2-20	98% - 1%	2-9	98% - 1%	1-6	97% - 9%	1-6	97% - 9%	3-19	99% - 19%	2-12	97% - 19%	1-8	95% - 22%		
Blicino	LNN1441N	230V50Hz			2-20	99% - 15%	2-20	98% - 17%	2-20	98% - 21%	2-20	98% - 21%	1-10	96% - 22%	1-10	97% - 26%	1-10	96% - 22%		
Blicino	LNN14408	230V50Hz	60-420	T	1-10	98% - 1%	2-14	98% - 16%	1-9	97% - 15%	1-9	97% - 15%	1-10	98% - 34%	1-10	97% - 35%	1-5	97% - 1%		
Blicino	NT4402N	230V50Hz	500	R	1-20	98% - 15%	1-13	98% - 20%	1-8	97% - 23%	1-8	97% - 23%	1-20	98% - 1%	1-10	98% - 5%	1-6	97% - 9%		
Busch-Jaeger	6513 U-102	230V50Hz	40-420	T	2-13	98% - 1%	1-10	98% - 5%	1-6	97% - 9%	1-6	97% - 9%	1-11	98% - 1%	1-10	99% - 1%	1-5	99% - 7%		
Busch-Jaeger	6523 U-102	230V50Hz	420	T	1-10	98% - 1%	1-10	99% - 1%	1-5	99% - 7%	1-5	99% - 7%	1-10	98% - 1%	1-10	99% - 1%	1-4	97% - 1%		
Busch-Jaeger	2250 U	230V50Hz	60-600	L	1-10	98% - 1%	1-10	98% - 1%	1-4	97% - 1%	1-4	97% - 1%	2-20	98% - 6%	1-20	98% - 7%	1-20	97% - 10%		
Busch-Jaeger	6526 U	230V50Hz			1-20	98% - 1%	1-13	97% - 1%	1-8	96% - 1%	1-8	96% - 1%	1-20	98% - 1%	1-13	97% - 4%	1-10	97% - 19%		
Busch-Jaeger	2247 U-500	230V50Hz	40-420	U	1-14	98% - 1%	1-13	97% - 4%	1-10	97% - 19%	1-10	97% - 19%								
CENTURY CONTROL	MULTI DIMMER	230V50Hz	60-600	L																
DINUY	RE EL1LE1	230V50Hz	400	LED																
ELKO	400GLI	230V50Hz																		
ELKO	315GLE	230V50Hz	20-315	T																
ELKO	600GLI	230V50Hz	40-600	U																
ELKO	420GLEI	230V50Hz	40-420	U																

Information about the LEDVANCE lamp type

Assessment of the results into categories. Includes the number of lamps and the related dimming range

DIMMER COMPATIBILITY LINE

BASISINFORMATIONEN:

1. WAS IST DER PRODUKTCODE UND WO FINDE ICH IHN?

Der Produktcode beschreibt den Lampentyp. Er besteht aus sieben Buchstaben und Ziffern und beginnt mit einem "A". Nachfolgend ein Beispiel eines Produktcodes auf dem Aufdruck der Lampe.



220-240V **AC01770** 2700K
13 W 50/60 Hz 27 mA
Made in Germany XXX-XXXX

2. WIE LESE ICH DIE FOLGENDEN TABELLEN?

Legende: Angaben zur Dimmbarkeit der Lampen. Grün bedeutet eine sehr gute Dimmbarkeit mit der angegebenen Lampenanzahl, gelb bedeutet eine eingeschränkte Dimmbarkeit, rot bedeutet, dass unerwünschtes dimmverhalten auftreten kann etc.

Liste der getesteten Dimmer

Legend					SUPERSTAR							
Very good dimmability with indicated number of lamps (dimming range greater than 75%)					PAR16 35 36*	PAR16 50 36*	PAR16 60 36*	PAR16 80 120*				
Limited dimmability with indicated number of lamps (dimming range smaller than 75%)												
Undesired dimmability					EAN/ Basic Code	EAN/ Basic Code	EAN/ Basic Code	EAN/ Basic Code				
Not relevant					405283330133/AC01184	405283330171/AC01187	405283330210/AB41305	405807503668/AC03049				
Not tested					405283330157/AC01192	405283330199/AC01194	405283330232/AB41306	405807503632/AC03051				
Dimmer					Number of Lamps	Dimming range	Number of Lamps	Dimming range	Number of Lamps	Dimming range	Number of Lamps	Dimming range
ABB	STD 50-3	230V50Hz	60-500	L	1-20	98% - 15%	1-13	98% - 20%	1-8	97% - 23%	1-8	97% - 23%
Altenburger Electronic	50 30	230V50Hz	15-350	T	2-20	98% - 15%	2-20	97% - 12%	2-20	98% - 16%	2-20	98% - 16%
AURORA	DSP 400	230V50Hz	400	L	1-10	98% - 15%	2-10	97% - 14%	1-4	96% - 1%	1-4	96% - 1%
Berker	2861	230V50Hz	50-420	U	1-20	98% - 27%	1-20	98% - 25%	1-20	97% - 27%	1-20	97% - 27%
Bicimo	LJNNT441N	230V50Hz			1-15	98% - 1%	1-10	97% - 5%	1-6	94% - 7%	1-6	94% - 7%
Bicimo	LJNNT4408	230V50Hz			2-20	98% - 1%	2-9	98% - 1%	1-6	97% - 3%	1-6	97% - 3%
Bicimo	NT4402N	230V50Hz	500	R	3-18	99% - 19%	2-12	97% - 19%	1-8	95% - 22%	1-8	95% - 22%
Busch-Jaeger	6513 U-102	230V50Hz	40-420	T	2-20	98% - 15%	2-20	98% - 17%	2-20	98% - 21%	2-20	98% - 21%
Busch-Jaeger	6523 U-102	230V50Hz	420	T	1-10	96% - 22%	1-10	97% - 26%				
Busch-Jaeger	2250 U	230V50Hz	60-600	L	1-10		2-14	98% - 16%	1-9	97% - 15%	1-9	97% - 15%
Busch-Jaeger	6526 U	230V50Hz			1-13	98% - 34%	1-10	97% - 35%	1-5		1-5	
Busch-Jaeger	2247 U-500	230V50Hz			1-20	98% - 15%	1-13	98% - 20%	1-8	97% - 23%	1-8	97% - 23%
CENTURY CONTROL	MULTI DIMMER	230V50Hz	60-600	L	2-13	98% - 1%	1-10	98% - 5%	1-6	97% - 9%	1-6	97% - 9%
DINJY	RE EL1LE1	230V50Hz	400	LED	1-11	98% - 1%	1-10	98% - 1%	1-5	99% - 7%	1-5	99% - 7%
ELKO	400GLI	230V50Hz			1-10		1-10		1-4	97% - 1%	1-4	97% - 1%
ELKO	316GLE	230V50Hz	20-315	T	2-20	98% - 6%	1-20	98% - 7%	1-20	97% - 10%	1-20	97% - 10%
ELKO	600GLI	230V50Hz	40-600	U	1-20	98% - 1%	1-13	97% - 1%	1-8	96% - 1%	1-8	96% - 1%
ELKO	420GLEI	230V50Hz	40-420	U	1-14	98% - 1%	1-13	97% - 4%	1-10	97% - 19%	1-10	97% - 19%

Angaben zum LEDVANCE Lampentyp

Bewertung der Testergebnisse in Ampel Kategorien. Beinhaltet sowohl die Lampenanzahl als auch den dimmbaren Bereich

DIMMER COMPATIBILITY LINE

Legend						LINE 75-95		LINE 95-100		LINE 110-100		LINE 110-100	
Good dimmability with indicated number of lamps													
Dimmability with indicated number of lamps (dimming range smaller than 75%)													
Undesired dimmability													
Not tested													
Brand	Model	Dimmer Voltage range	Power	Type	409807543252 / AC3219	409807543252 / AC3219	409807543256 / AC3219	409807543256 / AC3219	409807543256 / AC4578	409807543256 / AC4578	409807543254 / AC4578	409807543254 / AC4578	
					Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	
ABB	STD 50-3	230/50Hz	60-500	L	100-15%	100-15%	100-8%	100-12%	100-32%	100-14%	100-29%	100-29%	
Altenburger	50.3	230/50Hz			100-25%				100-23%	100-19%	100-22%	100-15%	
AURORA	DSP 400	230/50Hz	400	L	80-0%		88-0%		100-0%	100-0%	100-0%	100-0%	
Berker	2861	230/50Hz	50-420	U	100-15%	100-15%	100-12%	100-12%	100-29%	100-26%	100-27%	100-24%	
Bticino	L/N/NT4411 N HCA/D/HS44 11	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Bticino	L/N/NT4408 HCA/D/HS44 08	230/50Hz			100-0%	100-0%	100-0%						
bticino	NT4402N	230/50Hz	500	R					100-29%		100-29%	100-29%	
Busch-Jaeger	6513 U-102	230/50Hz	420	T	100-40%	100-40%	100-28%		100-29%	100-24%	100-27%	100-21%	
Busch-Jaeger	6523 U-102	230/50Hz	40-420	T			100-44%		100-6%	100-17%	100-9%	100-15%	
Busch-Jaeger	2250 U	230/50Hz	60-600	L					100-0%	100-0%	100-0%	100-0%	
Busch-Jaeger	6526 U	230/50Hz											
NTURY CONTMULTI DIMMER		230/50Hz	60-600	U	100-0%	100-0%	100-0%		100-0%	100-1%	100-0%	100-0%	
DimMax	420 SL	230/50Hz	200	L/T	100-0%	100-0%	100-0%	100-0%	100-6%	100-6%	100-5%	100-5%	
DINUY	RE.L1 LE1	230/50Hz	400	LED	100-0%	100-0%	100-0%	100-0%	100-6%	100-6%	100-4%	100-4%	
ELKO	400GLI	230/50Hz			75-0%		60-0%	72-0%		100-0%	100-0%	100-0%	
ELKO	315GLE	230/50Hz	20-315	T	100-0%	100-0%	100-0%	100-0%	100-6%	100-4%	100-5%	100-3%	
ELKO	600GLEA	230/50Hz			100-0%	100-15%	100-0%		100-12%	100-13%	100-10%	100-22%	
ELKO	600GLI	230/50Hz	40-600	U	100-0%		100-0%	92-0%	100-6%	100-7%	100-9%	100-16%	
ELKO	420GLEA	230/50Hz	40-420	U		100-0%		100-8%	100-6%	100-8%	100-6%	100-6%	
ELKO	1000LRI	230/50Hz			100-100%	100-100%	100-100%	100-100%					
ELKO	630GLE	230/50Hz	20-630	U	90-20%	100-15%	100-20%	100-12%	100-29%	100-25%	100-27%	100-21%	
Eitako	UD61NPN-LUC	230/50Hz	5-400	R/L/C	100-0%	100-0%	100-0%	100-0%	100-20%	100-20%	100-20%	100-17%	
Feller	40200 LEDxxx	230/50Hz			100-10%	100-10%	100-0%		100-26%	100-22%	100-26%	100-20%	
Feller	40600 RLC	230/50Hz	20-600	U	100-0%	100-15%	100-0%		100-12%	100-13%	100-10%	100-22%	
Feller	40600.RC	230/50Hz			90-20%	100-15%	100-20%	100-12%	100-29%	100-25%	100-27%	100-21%	
Feller	40600.RL	230/50Hz			100-0%		100-0%	92-0%	100-6%	100-7%	100-9%	100-16%	
Feller	40420.RLC	230/50Hz				100-0%		100-8%	100-6%	100-8%	100-6%	100-6%	
Feller	31000	230/50Hz			100-100%	100-100%	100-100%	100-100%					
Gira	226200	230/50Hz							100-1%	100-1%	100-1%	100-0%	
Gira	030700	230/50Hz	20-525	T	100-20%	100-15%	100-12%	100-8%	100-26%	100-23%	100-26%	100-20%	
Gira	117600	230/50Hz	50-420	U	100-20%				100-29%	100-28%	100-27%	100-24%	
Gira	238500	230/50Hz			100-0%		100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	
Gira	217400	230/50Hz	4X20-250	KNX-U	100-15%	100-15%	100-0%	100-12%	100-20%	100-14%	100-20%	100-15%	
Hager	WUD87	230/50Hz	400	LED-U	100-15%	100-15%	100-12%	100-12%	100-23%	100-20%	100-20%	100-17%	
Hamilton	KP1X40	230/50Hz	400						100-0%	100-0%			
Hugo Müller	adin 872110 I	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-6%	100-6%	100-4%	100-4%	
Jung	225 NVDE	230/50Hz	20-500	L		100-0%			100-1%	100-1%	100-1%	100-0%	
Jung	225 TDE	230/50Hz			100-20%	100-15%	100-12%	100-8%	100-26%	100-23%	100-26%	100-20%	
Jung	254 UDIE1	230/50Hz			100-20%				100-29%	100-28%	100-27%	100-24%	
Jung	1224 LEDUDE	230/50Hz		LED	100-0%		100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	
Jung	3904 REGHE	230/50Hz			100-15%	100-15%	100-0%	100-12%	100-20%	100-14%	100-20%	100-15%	
Legrand	665114	230/50Hz	400	U	100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Legrand	74319/57433	230/50Hz	400	U	100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Legrand	72239/57273	230/50Hz	400	U	100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Legrand	78407/87920	230/50Hz	400	U	100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Legrand	48869/04887	230/50Hz	400	U	100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Legrand	067803/048 869	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-3%	100-9%	100-4%	100-8%	
Legrand	099314	230/50Hz	300	RL				100-100%					
Legrand	770062	230/50Hz	400	RLC	100-0%	100-0%	100-0%	100-0%	100-3%	100-4%	100-2%	100-3%	
Legrand	078405	230/50Hz	600	RL	100-0%	100-0%	100-0%						

DIMMER COMPATIBILITY LINE

Legend					LINE 75 97C		LINE 75 100N		LINE 110 100E		LINE 110 100N	
Good dimmability with indicated number of lamps (dimming range greater than 75%)												
Limited dimmability with indicated number of lamps (dimming range smaller than 75%)												
Undesired dimmability												
Not tested												
					EAN / Code		EAN / Code		EAN / Code		EAN / Code	
					4058075432512 / AC32 130		4058075432536 / AC32 129		4058075432550 / AC45789		4058075432574 / AC45788	
Brand	Model	Dimmer Voltage range	Power	Type	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps
MASTER	DM-DGL	230/50Hz	1000	U/LED								
MASTER	DM-2500	230/50Hz	2500	U/LED	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Merten	1EGS136-000	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-6%	100-4%	100-5%	100-3%
Merten	1EGS134-000	230/50Hz			100-10%	100-10%	100-0%	100-0%	100-26%	100-22%	100-26%	100-20%
Merten	1EGS139-000	230/50Hz			100-0%	100-15%	100-0%	100-0%	100-12%	100-13%	100-10%	100-22%
Merten	1EGS137-000	230/50Hz			90-20%	100-15%	100-20%	100-12%	100-29%	100-25%	100-27%	100-21%
Merten	1EGS133-000	230/50Hz			100-0%	100-0%	100-0%	92-0%	100-6%	100-7%	100-9%	100-16%
Merten	1EGS138-000	230/50Hz			100-0%	100-0%	100-0%	100-8%	100-6%	100-8%	100-6%	100-6%
Merten	1EG 5170-030	230/50Hz	10-200	U	100-15%	100-15%	64-8%	64-8%	100-26%	100-20%	100-24%	100-0%
Merten	MEG 5131	230/50Hz	40-400	L	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Merten	MEG 5132	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Merten	MEG 5140	230/50Hz	9-100	L	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Merten	MEG 5135	230/50Hz	60-1000	L	100-100%	100-100%	100-100%	100-100%				
MK	K4501	230/50Hz	180	L	100-0%	100-15%	100-0%	100-12%	100-9%	100-9%	100-9%	100-10%
NEXUS	881P-01	230/50Hz	400	L	90-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
NIKO	310-01900 01901	230/50Hz	5-200	U	100-0%	100-0%	100-0%	100-0%	100-0%	100-4%	100-3%	100-3%
NIKO	330-00700 00701	230/50Hz	5-200	U	100-15%	100-15%	100-8%	100-8%	100-0%	100-0%	100-0%	100-0%
Odace	S520512	230/50Hz			100-10%	100-10%	100-0%	100-0%	100-26%	100-22%	100-26%	100-20%
Odace	S520511	230/50Hz			100-0%	100-0%	100-0%	92-0%	100-6%	100-7%	100-8%	100-16%
Odace	S520515	230/50Hz			100-0%	100-0%	100-0%	100-8%	100-6%	100-8%	100-6%	100-6%
Odace	S520518	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Osram	Ti DALI 315 DI	230/50Hz	20-315	DALI-T	100-0%	100-10%	100-0%	100-0%	100-13%	100-12%	100-12%	100-11%
PEHA	435 HAN	230/50Hz	60-600	L	70-10%	75-10%	60-4%	72-8%	81-9%	100-8%	100-7%	100-9%
Schneider	400GLJ	230/50Hz	40-400	T	75-0%	100-0%	60-0%	72-0%	100-0%	100-0%	100-0%	100-0%
Schneider	SBD315RC	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-6%	100-4%	100-5%	100-3%
Schneider	SBD200LED	230/50Hz	400		100-10%	100-10%	100-0%	100-0%	100-26%	100-22%	100-26%	100-20%
Schneider	SBD600RCRL	230/50Hz			100-0%	100-15%	100-0%	100-0%	100-12%	100-13%	100-10%	100-22%
Schneider	SBD630RC	230/50Hz			90-20%	100-15%	100-20%	100-12%	100-29%	100-25%	100-27%	100-21%
Schneider	SBD600RL	230/50Hz			100-0%	100-0%	100-0%	92-0%	100-6%	100-7%	100-9%	100-16%
Schneider	SBD420RCRL	230/50Hz			100-0%	100-0%	100-0%	100-8%	100-6%	100-8%	100-6%	100-6%
Schneider	5170	230/50Hz			100-15%	100-15%	64-8%	64-8%	100-26%	100-20%	100-24%	100-0%
Schneider	SBD400RL	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Schneider	SBDSP1	230/50Hz			100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
Schneider	ATTD1000RL	230/50Hz			100-100%	100-100%	100-100%	100-100%				
Shuttle	IM-T-LED-500	230/50Hz	2-500	T & LED-T	95-0%	95-0%	100-0%	100-0%	100-6%	100-7%	100-5%	100-29%
Siemens	5TC8 284	230/50Hz	20-525	T	100-0%	100-10%	100-0%	100-0%	100-14%	100-10%	100-12%	100-7%
Siemens	VG1-527-1AB	230/50Hz	20-500	KNX-U	100-0%	100-0%	100-100%	100-100%	100-0%	100-0%	100-0%	100-0%
theben	MAX 544 plus	230/50Hz	250	T	100-15%	100-15%	100-12%	100-0%	100-4%	100-20%	100-17%	100-18%
theben	IMAX 534 plu	230/50Hz	400	T	100-10%	100-10%	100-8%	100-8%	100-20%	100-41%	100-39%	100-37%
VADSBO	LD 220	230/50Hz	1-200	U	95-0%	100-0%	100-0%	100-0%				
VARLIGHT	HQ3W	230/50Hz	400		100-0%	100-0%	100-0%	100-0%	100-17%	100-17%	100-15%	100-0%
VARLIGHT	JP401W	230/50Hz	400	T	100-0%	100-0%	100-0%	100-12%	100-46%	100-46%	100-44%	100-41%
Vimar	20135	230/50Hz	3-100	U	100-0%	100-0%	100-0%	100-0%	100-29%	100-32%	100-30%	100-27%
ZANO	WH401	230/50Hz	400	L	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
ZANO	WH251	230/50Hz	250		100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%	100-0%
ZANO	Z GRID 500	230/50Hz	500		90-0%	100-0%	100-0%	100-0%	100-0%	100-1%	100-0%	100-0%

Please Note:

- The compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors. LEDVANCE does not take over any responsibility, warranty or liability that this results can also achieved by using the devices under other conditions, or when using successor models of the tested devices, or different models of the same manufacturer, or when using other LED lamp types
- The absence of a dimmer from this chart does not necessarily imply incompatibility.
- Please reference the dimmer manufacturer's instructions for installation.
- LED lamps contain several electronic components. Under unfavourable conditions these can lead to acoustic noise. In case of resonance even low noise can cause audible effect. Possible factors influencing this are the installation, the design of the lamp holder and the luminaire (acoustic resonance effect) as well as the dimmer or the transformer (harmonics or electronic resonance).
- Subject to change without notice
- Errors and omission excepted
- Always make sure to use the most recent release

Application Notes:

- For best dimming results trailing edge dimmer type is recommended.
- Trailing edge type dimmer requires the neutral wire for installation.

Bitte beachten:

- Die Kompatibilitätsliste basiert auf Tests, die der Hersteller in einer im Labor simulierten Umgebung durchgeführt hat. Die Ergebnisse können aufgrund verschiedener Faktoren in manchen Praxisanwendungen abweichen. LEDVANCE übernimmt keinerlei Verantwortung, Garantie oder Haftung dafür, dass diese Ergebnisse tatsächlich mit den Geräten unter anderen Bedingungen, mit Nachfolgemodellen der getesteten Geräte, mit anderen Modellen desselben Herstellers oder bei Verwendung anderer LED-Lampentypen erreicht werden.
- Das Fehlen eines Dimmers in der Abbildung bedeutet nicht, dass ein Dimmer nicht kompatibel ist.
- Lesen Sie stets die Installationsanweisungen des Dimmerherstellers.
- LED-Lampen bestehen aus mehreren elektronischen Komponenten. Unter ungünstigen Bedingungen können diese Störgeräusche erzeugen. Im Resonanzfall können selbst geringe Geräusche einen hörbaren Effekt hervorrufen. Einflussfaktoren können die Installation, die Gestaltung des Lampenträgers, die Leuchte (akustischer Resonanzeffekt), der Dimmer oder der Trafo (Oberschwingungen oder elektronische Resonanz) sein.
- Änderungen vorbehalten.
- Irrtümer und Auslassungen vorbehalten.
- Vergewissern Sie sich, dass Sie stets die aktuellste Version benutzen.

Anwendungshinweis:

- Um bestmögliche Dimmergebnisse zu erzielen, wird die Verwendung von Phasenabschnitt-Dimmern empfohlen.
- Phasenabschnitt-Dimmer erfordern bei der Installation einen Neutralleiter.

LEDVANCE GmbH

Head Office:

Parkring 1-5
85748 Garching, Germany
Phone +49 89 780673-100
Fax +49 89 780673-XXX
www.ledvance.com